HONDA GENERATORS

EB6500

Portable Gas Generator



www.atsequipment.com

This generator provides up to 6500 watts of commercial power. Standard features include automatic voltage regulator, Auto Throttle, G.F.C.I. receptacle and 120/240V operation. This unit also comes standard with a 2-wheel Transport Kit. The voltage selection switch allows for total generator output to be available through each of the 120 volt outlet for powering electric motors with large starting requirements (Output is limited to the rating of each receptacle).



SPECIFICATIONS

Engine Honda GX390

Engine, Horse Power 13 HP

Engine Type Single cylinder, overhead valve, air-cooled

Displacement 389cc

AC Output 120/240V 6500W max. (54.1/27.1A)

5500W rated (45.8/22.9A)

Receptacles C, E, F, H

DC Output N/A

Starting System Recoil

Fuel Tank Capacity 4.5 gals

Run Time per Tankful 5.3 hrs. @ rated load, 8.1 hrs. @ 1/2 load

Dimensions (L x W x H) 47.2" x 26.2" x 28.3"***

Noise Level 78 dB @ rated load

Dry Weight 217 lbs.

FEATURES

Honda OHV Engine

Oil Alert

Electric Ignition

Circuit breakers

Standard wheel kit

Automatic voltage

regulator

Full tubing frame for

protection

USDA-qualified spark arrester/muffler

Automatic Idle

120/240V selector switch

CFCI neutral bond

* RECEPTACLE KEY

RECEPTACLE DESCRIPTION PLUG #

B 15A 125V Duplex" 5-15P

C 20A 125V Duplex" 5-15P or 5-20P D 20A 125V GFCI Duplex" 5-15P or 5-20P E 20A 125V Locking Plug" L5-20P F 30A 125V Locking Plug" L5-30P G 20A 125/250V Locking Plug L14-20P H 30A 125/250V Locking Plug L14-30P I 50A 125/250V Locking Plug CS6365

ATS EQUIPMENT INC.

Construction Equipment & Supplies

Rentals • Sales • Service

BOSTON, MA (617) 825-3600 AUBURN, MA (508) 832-8500 REHOBOTH,MA (508) 379-6200 CANDIA, NH (603) 483-2100