

HONDA GENERATORS

EB5000

Portable Gas Generator

AVAILABLE FOR RENT AT



www.atsequipment.com

This generator provides up to 5000 watts of regulated power. Standard features include Steel Fuel Tank with 4-step filter, automatic voltage regulator, Auto Throttle, G.F.C.I. receptacle and 120/240V operation. Design for daily job site use, the full frame protection, standard bale hook, and 2 Wheel kit is the #1 choice of commercial users. The voltage selection switch allows for total generator output to be available through each of the 120-volt outlet for powering electric motors with large starting requirements (Output is limited to the rating of each receptacle).



SPECIFICATIONS

| | |
|------------------------|--|
| Engine | Honda GX340 |
| Engine, Horse Power | 11 HP |
| Engine Type | Single cylinder, overhead valve, air-cooled |
| Displacement | 337cc |
| AC Output | 120/240V 5000W max. (41.7/20.8A) 4500 rated 37.5/18.8A) |
| Receptacles | C, E, F, H |
| DC Output | N/A |
| Starting System | Recoil |
| Fuel Tank Capacity | 4.5 gals |
| Run Time per Tankful | 5.7 hrs. @ rated load, 8.5 hrs. @ 1/2 load |
| Dimensions (L x W x H) | 40.2" x 26.4" x 30.7"*** |
| Noise Level | 72 dB @ rated load |
| Dry Weight | 197 lbs. |

FEATURES

- Honda OHV Engine
- Oil Alert
- Electric Ignition
- Circuit breakers
- Standard wheel kit
- Automatic voltage regulator
- Full tubing frame for protection
- USDA-qualified spark arrester/muffler
- Automatic Idle
- 120/240V selector switch
- CFCI neutral bond

* RECEPTACLE KEY

RECEPTACLE DESCRIPTION PLUG #

B 15A 125V Duplex™ 5-15P

C 20A 125V Duplex™ 5-15P or 5-20P

D 20A 125V GFCI Duplex™ 5-15P or 5-20P

E 20A 125V Locking Plug™ L5-20P

F 30A 125V Locking Plug™ L5-30P

G 20A 125/250V Locking Plug L14-20P

H 30A 125/250V Locking Plug L14-30P

I 50A 125/250V Locking Plug CS6365

ATS EQUIPMENT INC. Construction Equipment & Supplies Rentals • Sales • Service

**BOSTON, MA
(617) 825-3600**

**AUBURN, MA
(508) 832-8500**

**REHOBOTH, MA
(508) 379-6200**

**CANDIA, NH
(603) 483-2100**